

Ad16 Series Pilot Lamp

Product Overview

Ad16 series pilot lamp only use LED lamp as the light source. The advantage have: long life, gentle weight, small cubage, save energy. It is the advanced product of all kinds of the incandescence lamp and the neon lamp of the XD type. The cover of the lamp is made of PC material, and have good shock resistance. It can be used as indication pilot light, accident signal and other signals in the circuits of such equipment as telecommunication.

Specifications

- ⊙ Electrical Life ≥ 30000 hours
- ⊙ Permitted Voltage $\pm 20\%$ ($\geq 110V$)
- ⊙ Dielectric Strength: $2.5kV(AC\ RMS), 1min$
- ⊙ Usage Frequency (AC): $50 \sim 60Hz$
- ⊙ Rated Operating Current: $\leq 20mA$
- ⊙ Brightness: $\geq 100cd/m^2$
- ⊙ Comparative Tracking Index $CT1 \geq 100$, flame retardant
- ⊙ Insulation Resistance: $U_i \leq 60V, 5M\Omega : 60V < U_i \leq 660V, 50M\Omega$
- ⊙ Light Color: red, green, yellow, white, blue, orange

Implication of Type

AD16	-	★	■	□	/	△	/	▲	/	●	/	◎
Code of series	The installation dimension of the neck: 16: $\Phi 16mm$ 22: $\Phi 22mm$	The design code (A, B, C, ... express different type of the same neck dimension) M buzzer S flicker SM flicker buzzer SS Dual-color lamp	S expresses the super short type, the standard type is without letter.	Color of pilot lamp: R red G green Y yellow O orange W white B blue	Voltage	K expresses anti-interference type, the normal type is without letter.	Protective Degree: P IP65 No letter means IP40					

Diagram of Interior Connection

	AC/DC Type Pilot Lamp	AC Type Pilot Lamp	AC/DC Type Dual-color Lamp	AC Type Dual-color Lamp
Normal Type				
Anti-interference Type				

Note: 1, AC/DC type pilot lamp is resistor step-down form; AC type pilot lamp is capacitor step-down form.

2. When voltage is 110V or above it, The temperature of outer shell of AC/DC type pilot lamp is higher than AC type pilot lamp.

Product Cutline($\Phi 22$)

Shape	Type Number	Color	Operating Voltage	Shape & Dimensions	Remarks
	AD16-22M/▲	Buzzer	AC/DC 6V AC/DC 12V AC/DC 24V AC/DC 36V AC/DC 48V		Sound Intensity: Volume $\geq 80\text{ dB}(10cm)$ Continuous Buzz Incontinuous Buzz $I_e \leq 35mA$
	AD16-22S/▲	Flicker Lamp	AC/DC 110V AC/DC 220V AC/DC 380V		
	AD16-22SM/▲	Flicker Buzzer	AC 110V AC 220V AC 380V		